

FRS / GMRS CHANNELS		
CH #	FREQ.	USEAGE
1	462.5625	FRS & GMRS
2	462.5875	FRS & GMRS
3	462.6125	FRS & GMRS
4	462.6375	FRS & GMRS
5	462.6625	FRS & GMRS
6	462.6875	FRS & GMRS
7	462.7125	FRS & GMRS
8	467.5625	FRS ONLY
9	467.5875	FRS ONLY
10	467.6125	FRS ONLY
11	467.6375	FRS ONLY
12	467.6625	FRS ONLY
13	467.6875	FRS ONLY
14	467.7125	FRS ONLY

GMRS REPEATERS	
REPEAT OUT	REPEAT IN
462.5500	467.5500
462.5750	467.5750
462.6000	467.6000
462.6250	467.6250
462.6500	467.6500
462.6750	467.6750
462.7000	467.7000
462.7250	467.7250
462.7500	467.7500

MURS FREQUENCIES		
CHANNEL #	FREQUENCY	BANDWIDTH
1	151.820	11.25 kHz
2	151.880	11.25 kHz
3	151.940	11.25 kHz
4 (Blue Dot)*	154.570	20.00 kHz
5 (Green Dot)*	154.600	20.00 kHz

STONE ISLAND	COBRA 250/300	CHEROKEE 465	MIDLAND 75-510	MOTOROLA SPORT	MOTOROLA TALK ABOUT	RADIO SHACK 106
67.0	1	1	1		1	1
69.3		2				
69.4						2
71.9	2	3	2		2	3
74.4	3	4	3		3	4
77.0	4	5	4	A	4	5
79.7	5	6	6		5	6
82.5	6	7	6		6	7
85.4	7	8	7		7	8
88.5	8	9	8	B	8	9
91.5	9	10	9		9	10
97.4	11	12	11	C	11	12
100.0	12	13	12		12	13
107.2	14	15	14	D	14	15
110.9	15	16	15		15	16
114.8	16	17	16		16	17
118.8	17	18	17	E	17	18
123.0	18	19	18		18	19
127.3	19	20	19	F	19	20
131.8	20	21	20		20	21
136.5	21	22	21		21	22
141.3	22	23	22	G	22	23
146.2	23	24	23		23	24
151.4	24	25	24		24	25

TONE	COBRA 250/300	CHEROKEE 465		MIDLAND 75- 510	MOTOROLA SPORT	MOTOROLA TALK ABOUT	RADIO SHACK 106
159.8		27					27
162.2	26	28		26		26	28
165.5							29
167.9	27	29		27		26	30
171.3							31
173.8	28	30		28		28	32
177.3							33
179.9	29	31		29		29	34
183.5		32					35
186.2	30	33		30		30	36
189.9		34					37
192.8	31	35		31		31	38
196.6		36					
199.5		37					
203.5	32	38		32		32	
206.5		39					
210.7	33	40		33		33	
218.1	34	41		34		34	
225.7	35	42		35		35	
229.1		43					
233.6	36	44		36		36	
241.8	37	45		37		37	
250.3	38	46		38		38	
254.1		47					

*Color Designations Left Over From Former Business Band Allocation